



<b>Product Code</b>	OSA-ACY-70033
<b>Description</b>	Rainjoy Lumos shower 480X330mm RGB LED front panel with AISI 304 stainless steel base plate included remote control & installation kit for false ceiling - Chromo therapy (RGB): LED 28.8W with 12V 3A Power Supply (SMPS) Including Controller, connecting to AC 100-240V, 50-60Hz - 2-functions - Rain - 4 X Mist
<b>Flow Rate</b>	Rain - 42.30 LPM @ 3 bar Mist - 2.40 LPM @ 3 bar
<b>Recommended Water Pressure</b>	2.0 - 4.0 Bar Min.
<b>Min &amp; Max Water Temperature</b>	5°C ~ 75°C
<b>Mount Type</b>	Ceiling Mounting
<b>Spray Modes</b>	Rain & Mist Functions
<b>Material Composition Specification in Percentage</b>	<b>STAINLESS STEEL:</b> Nickel 8.0-11.0, Chromium 18.0-20.0, Manganese 0.0 - 2.0, Carbon 0.0-0.08, Iron Remainder (AISI 304) <b>Acrylic:</b> Acrylic 6T = 6mm thick Acrylic sheet.
<b>REMOTE CONTROL</b>	<b>RGB Remote Control</b> Remote Option : RGB Working Voltage: 3Vd c Wireless Frequency: 2.4GHz Working Temperature: -5C-55C
<b>IP Rating</b>	1- LED Panel (IP4) 2- SMPS Box (IP7) which includes RGB controller inside
<b>LED Specification</b>	RGB LED Voltage : 12Vdc ( minimum electricity goes through LED panel for the user safety ) RGB LED Watt : 28.8W
<b>POWER SUPPLY</b>	Power Supply (SMPS) Including Controller INPUT : AC 100-240V, 50-60Hz OUTPUT : 12V - 3A
<b>RGB Color Variations</b>	<ul style="list-style-type: none"> <li>• COLOR VARIATION •</li> </ul> <div style="display: flex; justify-content: space-around; align-items: center;"> <div style="text-align: center;"> <p>Mono Color ( RGB )</p> </div> <div style="text-align: center;"> <p>Chromo Therapy</p> <p>LED On / Off Switch Sensor by Remote Control</p> </div> </div>

DISCLAIMER: Our every effort has been made to ensure factual accuracy, the information presented subject to changes due to requirements in different sites, markets and/ or countries. 10% variation in flow rate may be possible. Jaquar reserves the right to make the necessary amendments at any time without prior notice.